



C09-EE-408

**3479**

**BOARD DIPLOMA EXAMINATION, (C-09)**

**OCT/NOV—2015**

**DEEE—FOURTH SEMESTER EXAMINATION**

**ELECTRICAL ENGINEERING DRAWING**

*Time* : 3 hours ]

[ *Total Marks* : 60

---

**PART—A**

5×4=20

**Instructions** : (1) Answer **all** questions.

(2) Each question carries **five** marks.

(3) Drawing should be neat with necessary dimensions.

**1.** Draw the sectional elevation and side view of the end cover with bearing (not to scale).

**2.** Draw the free-hand sketch of yoke and pole assembly of 4-pole DC machine with inter poles.

**3.** Draw the sketch of 132 kV double-circuit tower.

**4.** Draw the single-line diagram of 220 kV/33 kV substation.

\*

**PART—B**

20×2=40

**Instructions** : (1) Answer *any two* questions.

(2) Each question carries **twenty** marks.

(3) Drawing should be neat with necessary dimensions.

**5.** (a) Draw the half-sectional side view of commutator assembly with the following data :

Diameter of the shaft = 46 mm

Diameter of the commutator = 111 mm

Height of the riser = 9.9 mm

Length of the V-notch = 50.8 mm

Length of the commutator = 88.9 mm

Thickness of the mica sheet = 0.8 mm

Distance between the two mica sheets = 3.5 mm

Assume the missing data if any.

(b) Draw the simple lap winding for a 24-conductor 2-pole DC machine with ring diagram and winding table.

**6.** Draw the full sectional elevation and sectional plan of a 500 kVA, 6600/400 V, single-phase core-type power transformer with the following dimensions :

Core type : Cruciform

Diameter of the circumcircle : 330

Height of core : 430

Center-to-center distance between cores : 490

Yoke height : 250

Yoke length : 770

Total height of the transformer : 990

Inside diameter of LT winding : 337

Outside diameter of LT winding : 383

Height of LT winding : 362

Inside diameter of HT winding  
1st layer : 415

\*

\*

Outside diameter of LT winding 1st winding	: 433
Inside diameter of HT winding 2nd layer	: 450
Outside diameter of LT winding 2nd layer	: 468
Height of HT winding	: 362

All dimensions are in mm. Assume any missing data.

7. Draw the following views of a 3- , 440 V, 50 Hz squirrel cage induction motor :

(a) Half-sectional front elevation

(b) Half-sectional end view

The dimensions are as follows :

Outside diameter of stator stampings = 230

Inside diameter of stator stampings = 164

Stator core length = 120

Thickness of stator frame = 25

**Stator slots :**

Type = open type

Number = 36

Size = 15 8

Air gap = 2

Outside diameter of rotor stampings = 160

Inside diameter of rotor stampings = 35

**Shaft diameter :**

At centre = 35

At bearing = 30

Total distance of footrest = 220

All dimensions are in mm. Assume any missing data if any.

\*\*\*

\*