

C09-M-606A

3784

BOARD DIPLOMA EXAMINATION, (C-09) OCT/NOV-2015

DME—SIXTH SEMESTER EXAMINATION

REFRIGERATION AND AIR-CONDITIONING

Time: 3 hours [Total Marks: 80

PART—A

 $3 \times 10 = 30$

Instructions: (1) Answer **all** questions.

- (2) Each question carries three marks.
- (3) Answers should be brief and straight to the point.
- **1.** State any three differences between open-air and closed-air refrigeration.
- 2. List out any six methods of refrigeration.
- 3. What is the function of flash chamber in a VCR system?
- **4.** Sketch T- diagrams for vapour compression cycle when the vapour after compression is (a) wet, (b) dry and (c) superheated.
- **5.** How vapour compression refrigeration system is better than the air refrigeration system?
- **6** Why is drier used before throttle value or capillary tube?
- 7. How do you classify the compressors?

- 8. Write any three differences between water-cooled and air-cooled condensers.
- **9.** Why is filter used in air conditioning system?
- **10.** Mention any three psychrometric processes.

PART—B

 $10 \times 5 = 50$

- **Instructions**: (1) Answer any **five** questions.
 - (2) Each question carries **ten** marks.
 - (3) Answers should be comprehensive and the criterion for valuation is the content but not the length of the answer.
- **11.** Explain the working of a Bell-Coleman refrigeration cycle with *P-V* and *T-* diagrams.
- **12.** In a 15 TR ammonia refrigeration plant, the condensing temperature is 25 °C and evaporating temperature is -10 °C. The refrigerant is subcooled by 5 °C before passing through throttle valve. The vapour entering the compressor is dry saturated. Find (a) COP and (b) power required.

The properties of ammonia are

Temperature °C	Enthalpy, kJ/kg		Entropy, kJ/kg °k		Specific heats	
	Liquid	Vapour	Liquid	Vapour	Liquid	Vapour
25	536.35	1703-2	4.593	8.509	4.6057	2.805
-10	375·15	1669.35	4.016	8.994	_	_

- **13.** (a) What are the differences between two-fluid and three-fluid absorption refrigeration system?
 - (b) Find out the ideal COP of the system in which heating, cooling and refrigeration takes place at temperatures of 110 °C, 25 °C and -12 °C respectively.
- **14.** Write the properties of following refrigerants :
 - (a) Ammonia
 - (b) Brine

- **15.** Describe cold storage with the help of a neat sketch.
- 16. (a) Explain the working of propeller fan with a neat figure.
 - (b) List out the applications of air conditioning.
- **17.** (a) What is psychrometric chart? What are the uses of psychrometric chart?
 - (b) The atmospheric conditions are 30 °C and specific humidity of 12.5 grams/kg of air. Determine the following:
 - (i) Partial pressure of air
 - (ii) Relative humidity
 - (iii) DPT
- 18. Explain the Winter Air Conditioning System with a neat sketch.

* * *